



## One Camera, 16 Channel Transmitter

### IV-5800TR

#### Features:

- . Use worldwide 5.8GHz ISM band
- . 16 Channels PLL Synthesizer
- . Connect to DVD/TV/DVR/Quad/Camera no messy cables
- . Reach highly efficient FM-FM modulation/demodulation scheme



SPECIFICATION	IV-5800TR
Operation Frequency	5645 ~ 5945MHz
Channel Selection	PLL Synthesizer 16 Channel
Channel Frequency	CH1: 5945MHz CH2: 5925MHz CH3: 5905MHz CH4: 5885MHz CH5: 5865MHz CH6: 5845MHz CH7: 5825MHz CH8: 5805MHz CH9: 5785MHz CH10: 5765MHz CH11: 5745MHz CH12: 5725MHz CH13: 5705MHz CH14: 5685MHz CH15: 5665MHz CH16: 5645MHz
Video-Audio Demodulation	FM
Carrier Frequency Accuracy	±300KHz
Output Power	1000mW(1Watt)
Transmission Range	3600 feet(Open Site)
Antenna	Omni-directional Antenna Gain 5dBi
Output Impedance	50 Ohm SMA Connector
Video Input Level	1 Vp-p, 75Ω
Audio Input Level	1 Vp-p, 600Ω
Power Supply	DC12V / 0.5A for AC Adaptor
Dimension	4" x 3" 1.3" (110 x 75 x 23mm)